HIGH-SPEED
BANKNOTE COUNTER



DUST COLLECTING DEVICE

SELF CLEANING

COUNTER

plus



- Automatic Counting function Automatically Counting start with putting the notes in the clamper
- ALARM function when the counted notes are more or less than 100 notes, this function will be operated with Alarm signal and sound .
- PRESET function available for counting the preseted numbers of notes by just pressing any key button on the 10 key panel.
- ADD function available for accumulating the numbers of counted notes
- SELF CLEANING FUNCTION by Air
- DUST COLLECTING DEVICE for efficient dust removal
- Optional Customer Display
- Auto Stamping (OK) function per 100 notes (OPTION)

PLUS CO., LTD.

http://www.plus.co.kr/eng

FEATURES

- Automatic Counting function—Automatically Counting start with putting the notes in the clamper
- ALARM function—when the counted notes are more or less than 100 notes, this function will be operated with Alarm signal and sound.
- PRESET function-available for counting the preseted numbers of notes by just pressing any key button on the 10 key panel.
- · ADD function-available for accumulating the numbers of counted notes
- SELF CLEANING FUNCTION by Air
- DUST COLLECTING DEVICE for efficient dust removal.
- Optional Customer Display.
- Auto Stamping (OK) function per 100 notes (OPTION)

SPECIFICATION

Dimention	370(W)mm×805(H)mm×300(D)mm
Weight	Approximately 40Kgs
Counting Speed	100notes/4sec
Size of Countable Note	50mm×100mm~100mm×180mm
	Thickness: 0.06mm~0.12mm
Feeding System	Vacuum Suction Spindle type
Clamper Capacity	200notes
Large Display for counting	4digits
Preset Display	3digits
Power Source	AC 110/220V, 50/60Hz
Power Consumption	400W

▶We reserve the rights to change specifications and design without notice

DISPLAY PANEL

- · Simple and easy operational function keys
- Large LED display of 4digits for displaying the counted numbers and Preset display of 3digits
- Accurate and Quiet counting at high speed up to 100 sheets per 4seconds

